MIX
Paper made from recycled material
FSC® C167436

Power Bank P64-P1 25000mAh / 140W

USER MANUAL



Press to check the power level

- DE Drücken Sie, um den Energiestatus zu überprüfen
- IT Premere per controllare il livello di carica
- ES Presiona para verificar el nivel de energía
- FR Appuyez pour vérifier le niveau de charge
- JA 電力レベルを確認するために押してください
- NL Druk om het energieniveau te controleren
- SV Tryck för att kontrollera strömnivån
- PL Naciśnij, aby sprawdzić poziom naładowania
- AR اضغط للتحقق من مستوى الطاقة



1. Output Power

- DE Ausgangsleistung
- IT Potenza in uscita
- ES Potencia de salida
- FR Puissance de sortie
- JA 出力
- NL Uitgangsvermogen
- SV Uteffekt
- PL Moc wyjściowa
- AR انتاج الطاقة



2. Remaining Battery

- DE Verbleibende Leistung
- IT Potenza residua
- ES Energía restante
- FR Puissance restante
- JA 残りの電力
- NL Overblijvende energie
- SV Återstående effekt
- PL Pozostała moc
- AR القوةالمتبقية



3. Remaining Battery in Hrs

- DE Verbleibende Batterielaufzeit (Std.)
- IT Batteria residua (ore)
- ES Batería restante (horas)
- FR Autonomie restante (heures)
- JA 残りのバッテリー時間
- NL Resterende batterij (uren)
- SV Återstående batteritid (timmar)
- PL Pozostała bateria (godz.)
- AR البطاريةالمتبقيةبالساعات



Double-click to toggle USB output power display

- DE Doppelklicken, um die Anzeige der USB-Ausgangsleistung umzuschalten.
- IT Doppio clic per alternare la visualizzazione della potenza di uscita USB.
- ES Haz doble clic para alternar la visualización de la potencia de salida USB.
- FR Double-cliquez pour basculer l'affichage de la puissance de sortie USB.
- JA USB出力電力表示を切り替えるにはダブルクリックしてください。
- NL Dubbelklik om het USB-uitgangsvermogen weer te geven.
- SV Dubbelklicka för att växla visning av USB-utgångseffekt.
- PL Kliknij dwukrotnie, aby przełączyć wyświetlanie mocy wyjściowej USB.
- AR انقر نقرًا مزدوجًا لتبديل عرض طاقة إخراج USB



Press 3s to switch between Pro & EZ modes

- DE Drücken Sie 3 Sekunden lang, um zwischen Pro- und EZ-Modus zu wechseln.
- IT Premere per 3 secondi per passare tra le modalità Pro ed EZ.
- ES Presiona 3 segundos para cambiar entre los modos Pro y EZ.
- FR Appuyez pendant 3 secondes pour passer entre les modes Pro et EZ.
- JA 3秒押してProモードとEZモードを切り替える。
- NL Druk 3 seconden om te wisselen tussen Pro en EZ modus.
- SV Tryck i 3 sekunder för att växla mellan Pro- och EZ-lägen.
- PL Przytrzymaj przez 3 sekund, aby przełączyć między trybami Pro i EZ.
- AR اضغط على 3 للتبديل بين وضعي Pro وEZ

Contact Us

Kontaktieren Sie uns | Contattaci | Contáctenos | Contactez-nous | お問い合わせ | Contact | Kontakta oss | Kontakt | اتصل بنا

US/CA **+1 833-945-5803**
Hours: Mon-Fri, 9 AM - 6 PM (EST)
(activate "International Roaming" service if you are in CA)

DE **+498954194787**
Hours: Mon-Fri, 9 AM - 6 PM

UK **+442045576762**
Hours: Mon-Fri, 9 AM - 6 PM

support@iniu.shop

iniushop.com

@iniuofficial

iniu_official



Use a suitable USB port to charge (LED off after 6-min)

- DE Zum Laden geeigneten USB-Anschluss nutzen (LED aus nach 6 Min).
- IT Usa una porta USB adatta (LED spento dopo 6 min).
- ES Usa un puerto USB adecuado (LED apagado tras 6 min).
- FR Utilisez un port USB approprié (LED éteinte après 6 min).
- JA 適切なUSBポートで充電（6分後にLED消灯）。
- NL Geschikte USB-poort gebruiken (LED uit na 6 min).
- SV Använd rätt USB-port (LED av efter 6 min).
- PL Użyj odpowiedniego USB (LED wyłącza się po 6 min).
- AR استخدم منفذ USB مناسب (LED تطفأ بعد ٦ دقائق).

Specifications

Spezifikationen | Specifiche | Especificaciones | Spécifications | 仕様 | Specificaties | Specifikationer | Specyfikacje | تحديد

Model Number	P64-P1
Capacity	25000mAh / 92.5Wh
Battery Type	Lithium Battery
Size	6.3*3.2*1.0in / 15.9*8.2*2.6cm
Weight	17.5oz / 495.5g
Input	USB-C1: 5V ⎓3A, 9V ⎓3A, 15V ⎓3A, 20V ⎓4A, 28V ⎓2.85A (80W max)
Output	USB-C1: 5V ⎓3A, 9V ⎓3A, 12V ⎓3A, 15V ⎓3A , 20V⎓5A, 28V ⎓5A (140W max) USB-C2: 5V ⎓3A, 9V ⎓3A, 12V ⎓3A, 15V ⎓3A (45W max) USB-A: 5V ⎓3A, 9V ⎓2A, 12V ⎓1.5A (18W max)
Fast Charging Protocol	PD3.1, PD3.0, PD2.0, QC3.0, QC2.0, PPS, AFC, etc.

MADE IN CHINA

3 YEARS WARRANTY

- DE 3-Jahres-Garantie
- IT Garanzia di 3 anni
- ES Garantía de 3 años
- FR Garantie de 3 ans
- JA 3年保証
- NL 3-jarige garantie
- SV 3 års garanti
- PL Gwarancja 3-letnia
- AR ضمان لمدة ٣ سنوات

LIFETIME TECHNICAL SUPPORT

- DE Lebenslanger technischer Support
- IT Supporto tecnico a vita
- ES Soporte técnico de por vida
- FR Assistance technique à vie
- JA 終身技術サポート
- NL Levenslange technische ondersteuning
- SV Livstid teknisk support
- PL Wsparcie techniczne na całe życie
- AR الدعم الفني مدى الحياة

This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health form uncontrolled waste disposal .recycle it responsibly to promote the sustainable reuse of material resources. To return your used device .please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

WARNINGS

- EN Do not disassemble or modify
  Do not short-circuit
  Do not dispose in fire
  Do not expose to high-temperature
- DE Nicht zerlegen oder modifizieren
  Nicht kurzschließen
  Nicht im Feuer entsorgen
  Nicht hohen Temperaturen aussetzen
- IT Non smontare o modificare
  Non cortocircuitare
  Non gettare nel fuoco
  Non esporre ad alte temperature
- ES No desensamblar ni modificar
  No cortocircuitar
  No desechar en el fuego
  No exponer a altas temperaturas
- FR Ne pas démonter ni modifier
  Ne pas court-circuiter
  Ne pas jeter au feu
  Ne pas exposer à des températures élevées
- NL Niet demonteren of modificeren
  Niet kortsluiten
  Niet in het vuur gooien
  Niet blootstellen aan hoge temperaturen
- SV Demontera eller modifiera inte
  Kortslut inte
  Kassera inte i eld
  Utsätt inte för höga temperaturer
- PL Nie demontować ani modyfikować
  Nie zwierać
  Nie wyrzucać do ognia
  Nie wystawiać na działanie wysokiej temperatury
- TR Sökme veya değiştirme
  Kısa devre yapma
  Ateşe atma
  Yüksek sıcaklıklara maruz bırakma

UK REP
Sea&Mew Accounting Ltd
Electric Avenue Vision 25, London, Enfield EN3 7GD

EC REP
GAVIMOSA CONSULTORIA, SOCIEDAD LIMITADA
CASTELLANA 9144, 28046 Madrid

Manufacturer/Importer: Shenzhen Topstar Industry Co., Ltd.
Address: Room 929 , Jiaoye Plaza, No.318, Minzhi Avenue, Minzhi Community, Minzhi Street, Longhua District, Shenzhen CN 518131