



Camera Models:

SRXE4-2V12-EBT-IR1	SRXE4-4V9-EBT-IR1	SRXE4-6V9-EBT-IR1	SRXE4-8V9-EBT-IR1
SRXE4-2X33-EBT-IR1	SRXE4-4X31-EBT-IR1	SRXE4-6X31-EBT-IR1	SRXE4-8X31-EBT-IR1
	SRXE4P-4V9-EBT-IR1		SRXE4P-8V9-EBT-IR1
	SRXE4P-4X31-EBT-IR1		SRXE4P-8X31-EBT-IR1

Document number: C6755M

Publication date: 2025-04-25

Legal Notices

© 2025, Pelco Corporation. All rights reserved. PELCO, the PELCO logo, PELCO are trademarks of Pelco Corporation. ONVIF is a trademark of Onvif, Inc. Covered by one or more claims of the patents listed at patentlist.hevcadvance.com. Other names or logos mentioned herein may be the trademarks of their respective owners. The absence of the symbols ™ and ® in proximity to each trademark in this document or at all is not a disclaimer of ownership of the related trademark. Pelco Corporation protects its innovations with patents issued in the United States of America and other jurisdictions worldwide (see www.pelco.com). Unless stated explicitly and in writing, no license is granted with respect to any copyright, industrial design, trademark, patent or other intellectual property rights of Pelco Corporation or its licensors.

Disclaimer

This document has been compiled and published using product descriptions and specifications available at the time of publication. The contents of this document and the specifications of the products discussed herein are subject to change without notice. Pelco Corporation reserves the right to make any such changes without notice. Neither Pelco Corporation nor any of its affiliated companies: (1) guarantees the completeness or accuracy of the information contained in this document; or (2) is responsible for your use of, or reliance on, the information. Pelco Corporation shall not be responsible for any losses or damages (including consequential damages) caused by reliance on the information presented herein.

Pelco Corporation

www.pelco.com

C6755M

Revision: 5 - EN

20250425

Important Safety Information



WARNING

Failure to observe the following instructions may result in severe injury or death.

- Installation must be performed by qualified personnel only, and must conform to all local codes.
- Any external power supply connected to this product may only be connected to another Pelco product of the same model series. External power connections must be properly insulated.
- Do not connect directly to mains power for any reason.



CAUTION

Failure to observe the following instructions may result in injury to persons or damage to the device.

- Do not expose the camera directly to high levels of x-ray, laser, or UV radiation. Direct exposure may cause permanent damage to the image sensor.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other sources of heat.
- Do not subject the device cables to excessive stress, heavy loads or pinching.
- Do not open or disassemble the device. There are no user serviceable parts.
- Refer all device servicing to qualified personnel. Servicing may be required when the device has been damaged (such as from a liquid spill or fallen objects), has been exposed to rain or moisture, does not operate normally, or has been dropped.
- Do not use strong or abrasive detergents when cleaning the device body.
- Use only accessories recommended by Pelco.

Regulatory Notices

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This Class B digital apparatus complies with CAN ICES-003(B)/NMB-003(B)

This device complies with EN 60529 IP66 and IP67 rating.

This device complies with EN 60529 IP66, IP67 and IP68 rating.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment contains a coin cell battery. WARNING: Risk of fire, explosion, and burns. Do not disassemble, crush, heat above 100°C (212°F), or incinerate.

The use of EMC compliant support and auxiliary equipment with this device is required in order to fully comply with the EMC regulatory standards.

This product is intended to be supplied by a UL Listed Power Unit marked "Class 2" or "LPS" or "Limited Power Source" with output rated 12-24 VDC, 25 W max. or Power over Ethernet (PoE), 25 W max.

UK Product Security and Telecommunications Infrastructure (PSTI) Act: Pelco cameras comply with the PSTI requirements. For more information, see the published [PSTI Statement of Compliance](#).

For Korea

이 기기는 가정용(B급) 전자파적합기기로서 주로 가정에서 사용하는 것을 목적으로 하며, 모든 지역에서 사용할 수 있습니다.

IR Safety Information



RISK GROUP 2 | CAUTION
IR emitted from this product.

GROUPE DE RISQUE 2 | ATTENTION
IR émis par ce produit.

Avoid eye exposure. Use appropriate shielding or eye protection.

Disposal and Recycling Information

When this product has reached the end of its useful life, please dispose of it according to your local environmental laws and guidelines.

European Union:



This symbol means that according to local laws and regulations your product should be disposed of separately from household waste. When this product reaches its end of life, take it to a collection point designated by local authorities. Some collection points accept products for free. The separate collection and recycling of your product at the time of disposal will help conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment.

Table of Contents

Important Safety Information	3
Regulatory Notices	4
For Korea	5
Overview	1
Junction Box View	1
Rear View	1
Front View	2
Configuration Panel View	2
Side View	3
Installing a Product_Name	4
Pre-Deployment In-Box Configuration	4
Camera Package Contents	5
Sarix Enhanced 4 and 4P Bullet Installation Steps	6
Mounting and Aiming Video Analytics Cameras	6
Installing the Junction Box	6
Accessing Cables through the Side Conduit	8
Connecting Cables	9
Mounting the Camera	11
Aiming the Camera	11
Removing the Configuration Panel Cover	13
Initializing a Camera by Creating a Username and Password	13
Using the USB Wi-Fi Adapter	13
Assigning an IP Address	14
Accessing the Live Video Stream	14
Zooming and Focusing the Camera	15
(Optional) Enabling the Microphone	16
(Optional) Configuring the Microphone	16
Configure the Microphone from the Camera Web Interface	16
(Optional) Configuring microSD Card Storage	16
Configuring the Camera	17
For More Information	17
Connecting to Power and External Devices	18
External Power Failover	19
Non-Seamless Failover for SRXE4 models	19
Seamless Failover for SRXE4P models	19

Sarix Enhanced 4 and 4P Bullet Cameras Installation Manual

Connection Status LED Indicators 21

 Troubleshooting Network Connections and LED Behavior 21


Resetting to Factory Default Settings 23

Limited Warranty and Technical Support 24

Pelco Troubleshooting Contact Information 25


Overview

Junction Box View



1. **Camera Mounts**
Points for installing the camera to the mounting bracket.
2. **Mounting hinge**
Point to hold the camera to the junction box while connecting the required cables.
3. **Cable hooks**
Points to wrap the excess cable length around.
4. **Mounting holes**
Holes for securing the mounting bracket to the mounting surface.

Rear View



1. **Camera mounting screws**
Screws for mounting the camera to the junction box.
2. **Power and I/O cable connectors**
Cable connectors for connecting the camera cables to auxiliary power and I/O devices. For more information, see [Connecting to Power and External Devices on page 18](#).
3. **Ethernet port**

Sarix Enhanced 4 and 4P Bullet Cameras Installation Manual

Accepts an Ethernet connection to a network. Server communication and image data transmission occurs over this connection. Also receives power when it is connected to a network that provides Power over Ethernet.


4. Regulatory tag

Provides regulatory information.

5. Mounting hooks

Hooks to attach the camera to the junction box while connecting the required cables.

Front View



1. Microphone

Built-in microphone records audio when enabled. For more information, see [\(Optional\) Enabling the Microphone on page 16](#).




NOTE

Microphone is not available on SRXE4P camera models.

2. Configuration panel cover

Covers the configuration panel. For more information on the configuration panel, see the [Configuration Panel View below](#).

Configuration Panel View



1. Microphone switch

Switch to enable or disable the built-in microphone. For more information, see [\(Optional\) Enabling the Microphone on page 16](#).



NOTE

Microphone is not available on SRXE4P camera models.

2. microSD card slots (x2)

Accepts up to two microSD cards for onboard storage. Install microSD cards so the metal contacts are facing upward. For more information, see [\(Optional\) Configuring microSD Card Storage on page 16](#).


3. Connection status LED indicators

Provides information about device operation. For more information, see [Connection Status LED Indicators on page 21](#).

4. USB-C

Accepts a USB type-C to USB adapter. Only required when using the USB Wi-Fi Adapter. For more information, see [Using the USB Wi-Fi Adapter on page 13](#).

Side View



1. Sun shroud

A cover to help protect the lens against glare from the sun.

2. Mount arm

Adjustable mount arm for positioning the camera.

3. Adjustment screws

Provides a locking mechanism for the mount arm.

Installing a Product_Name

Pre-Deployment In-Box Configuration


The camera comes equipped with an RJ45 connector that is accessible from the outside of the box for users that want to configure camera settings before installing the camera. The RJ45 connector is accessible through the small flap on the side of the camera box for easy configuration before unpacking the camera.



NOTE

We recommend that you do not exceed 3 hours of leaving your camera connected during inbox configuration with ambient temperatures between 20 °C - 25 °C (68 °F - 77 °F).

1. Locate and open the flap on the side of the camera packaging. Look for the *Config* label:



2. Connect a network cable to the RJ45 plug on the configuration cable. The network cable must provide PoE power, IEEE 802.3af Class 3, to power the camera during configuration.
3. Connect to the camera using the Camera Configuration Tool, or the camera's web browser interface to configure the camera's settings. For more information about connecting to the camera, see [Assigning an IP Address on page 14](#), and [Accessing the Live Video Stream on page 14](#).
4. Once you have finished making configuration changes, unplug the network cable.



CAUTION

Be careful when handling the camera after configuring it inside the packaging. The camera may be hot when handling it or removing from the packaging immediately after in-box configuration.

Camera Package Contents

- Pelco SRXE4 or SRXE4P Bullet Camera
- Mounting template sticker
- 4 screws and anchors for solid walls
- T20 Pin-In star-shaped driver
- Junction Box
- Wall plate
- Aux terminal block
- I/O Terminal Block
- 1/2" conduit adapter
- Grommet piercing cap

Sarix Enhanced 4 and 4P Bullet Installation Steps

Mounting and Aiming Video Analytics Cameras

Follow these guidelines when mounting and aiming Brand_Name cameras for best results:


- **Height** – Above 2.74 meters (9 feet).
- **Tilt** – Downward tilt of 45 degrees maximum.
- **Level** – Keep the camera image level with the horizon.
- **Stability** – Securely mount to a stable surface to prevent movement.

For more information, see *Designing a Site with Pelco Smart Analytics* available at pelco.com/docs.


Installing the Junction Box

When installing the junction box, the cables for the camera can be accessed through either a hole in the wall or from a side conduit entry into the junction box. If your installation requires a side conduit to access the required cables, refer to [Accessing Cables through the Side Conduit on page 8](#).


1. Use the mounting template to drill four mounting holes into the mounting surface.



2. Drill the cable entry hole into the mounting surface then pull the required cables through the cable entry hole.




3. Fasten the junction box to the mounting surface and pull the cords through.



NOTE


It is recommended that silicone sealant be applied around the edge of the junction box to prevent moisture from entering the mounting surface.

4. Hook the camera onto the junction box using the mounting hooks, and let the camera hang.




Accessing Cables through the Side Conduit


1. Use the mounting template to drill four mounting holes into the mounting surface.




2. Secure the conduit pipe in place using a pipe clamp.



3. Pull the cables through the conduit and wrap the excess cable length around the cable hooks.




4. Fasten the cable with a zip tie.
5. Fasten the junction box to the mounting surface and pull the cords through.



NOTE

It is recommended that silicone sealant be applied around the edge of the junction box to prevent moisture from entering the mounting surface.


6. Hook the camera onto the junction box using the mounting hooks, and let the camera hang.




Connecting Cables

(missing or bad snippet)


1. If there are external input or output devices that need to be connected to the camera (for example: door contacts, relays, etc.), connect the devices to the camera's digital I/O connector cables. For more information see [Connecting to Power and External Devices on page 18](#).
2. If an external microphone and/or speakers need to be connected to the camera, connect the devices to the camera's audio I/O cables. For more information, see [Connecting to Power and External Devices on page 18](#).
3. Pull the cables through the wall or side conduit.
4. Put the piercing cap through on the ethernet cable and push it through the grommet.



5. Thread the cable through the junction box and sit the grommet in the cable hole of the junction box.



6. Connect a network cable to the Ethernet port (RJ-45 connector).
The Link LED indicator will turn on once a network link has been established.




7. Connect power using one of the following methods:
 - Power over Ethernet (PoE) Class 3 or Class 4 – If PoE is available, the camera LEDs will turn on.
 - External Power – Connect an external 12 V DC to the terminal block.
8. Check that the Connection Status LED indicator indicates the correct state. For more information, see [Connection Status LED Indicators on page 21](#).

Mounting the Camera

Once all the cable connections have been made, secure the camera to the mounting bracket.


1. Tuck the extra lengths of cables into the cable entry hole.
2. Secure the camera to the mounting bracket:
 - a. Raise the camera until it covers the mounting bracket.
 - b. Use the camera mounting screws to fasten the camera to the bracket.




Aiming the Camera

Reference the camera's live stream as you aim the camera.

1. To aim the camera, loosen the adjustment screws on the camera mount arm.



2. Rotate and move the camera and mount arm as required. Review the camera's live video stream to help aim the camera correctly.



3. To use the camera in portrait mode instead of landscape mode:


- a. Use a T20 Pin-In star-shaped driver to unscrew and remove the sun shroud mount from the camera.



NOTE


The sun shroud should only be removed when the camera is installed indoors and space is limited.

- b. Rotate the camera.



- c. Use a T20 Pin-In star-shaped driver to screw on the sun shroud mount.


4. Tighten the adjustment screws on the mount arm to secure the camera's position.



5. In the camera web browser interface, adjust the camera's Image and Display settings. You can set the zoom position, focus and change the image rotation.

Removing the Configuration Panel Cover

1. Use a T20 Pin-In star-shaped driver to unscrew the configuration panel cover.



2. Remove the cover from the configuration panel.

Initializing a Camera by Creating a Username and Password

You must create an initial user with administrator privileges and log in to the camera before the camera becomes operational. You will need the camera's IP address to create the initial user. See [Discovering Cameras on the Network on page 1](#) for instructions on how to obtain the camera's IP address.

There are different tools you can use to create the initial user. See [Choose a Tool to Discover, Initialize and Configure Cameras on page 1](#) for more information.

You can use one of the following tools to create the initial user:

- **Camera Configuration Tool** – cameras discovered in the factory default state will be identified by . Select the *Admin Users* tab to create the first user.
- **Camera Web Interface** – enter the camera's IP address in a web browser to access the web interface. If the camera is in the factory default state you will be redirected to the *Add a new user* page to create the first user.



NOTE

If you are using a third-party VMS, you must complete this step with either CCT or the camera's web interface before you can use the camera.

Using the USB Wi-Fi Adapter

You can use the USB Wi-Fi Adapter to connect the camera to the network instead of an Ethernet cable. This camera required either the USB-AC56-NA-MSI-B or USB-AC56-EU-MSI-B adapter.

1. Attach the adapter to the camera's USB-C port to add the camera to the network.
2. Open the camera's mobile web interface.
3. After you connect to the Wi-Fi signal broadcast by the adapter, you can access the mobile web interface from any mobile device using the following address: `http://camera.lan`.



NOTE

The camera will reserve the 10.11.22.32/28 subnet for internal use while the USB Wi-Fi Adapter is plugged in.

4. You can also use the mobile web interface to configure the camera settings. For more information about configuring the camera from the mobile web interface, see the [USB Wi-Fi Adapter System User Guide](#).

Assigning an IP Address

The device automatically obtains an IP address when it is connected to a network.



NOTE

If the device cannot obtain an IP address from a DHCP server, it will use Zero Configuration Networking (Zeroconf) to choose an IP address. When set using Zeroconf, the IP address is in the 169.254.0.0/16 subnet.

The IP address settings can be changed using one of the following methods:

- Device's web browser interface: `http://<camera IP address>/`.
- Network Video Management software application.



NOTE

When you log in the first time, the camera will be in a factory default state and no password is required. You must create a user with **administrator** privileges before the device is operational. For more information, see [Initializing a Camera by Creating a Username and Password on the previous page](#).

Accessing the Live Video Stream

Live video stream can be viewed using one of the following methods:

- Web browser interface: `http://< camera IP address>/`.
- Network Video Management software application.



NOTE

When you log in the first time, the camera will be in a factory default state and no password is required. You must create a user with **administrator** privileges before the device is operational. For more information, see [Initializing a Camera by Creating a Username and Password on the previous page](#).

Zooming and Focusing the Camera


- In the camera web browser interface, use the camera's Image and Display settings to zoom and focus the camera.
 - a. Use the zoom buttons to zoom the camera in or out.
 - b. Click **Auto Focus** to focus the lens.
 - c. Use the focus near and far buttons to manually adjust the focus.

(Optional) Enabling the Microphone

The Sarix Enhanced 4 camera models feature an internal microphone, and include a switch to physically enable or disable the microphone. The microphone switch is set to OFF by default.

We recommend that you enable the microphone before installing the camera in its final location.

1. Locate the microphone switch on the camera assembly.
2. Slide the switch from the default OFF position to ON to enable the microphone.



(Optional) Configuring the Microphone

You can configure the microphone or line-level audio input from the camera web interface.

Configure the Microphone from the Camera Web Interface

- In the camera web interface, the microphones are configured from the *Audio* page. You can adjust the microphone volume by changing the gain.
 - Gain for microphone Internal Mic – configures the gain for the microphone that is built into the camera.
 - Gain for microphone External Input – configures the gain for any line level audio input that is connected to the audio input connector on the I/O terminal block.

For instructions on how to configure the microphone from your camera's web interface, refer to [Pelco > Product documentation](#) and search for the relevant Operations Manual for the camera type.

(Optional) Configuring microSD Card Storage

To use the camera's onboard storage feature, you must insert 1 microSD card into a microSD card slot.

It is recommended that the microSD card have a write speed of class 10 or better. If the microSD card does not meet the recommended write speed, the recording performance may suffer and result in the loss of frames or footage.

1. Insert a microSD card into the camera.



CAUTION

Do not force the microSD card into the camera or you may damage the card and the camera. The microSD card can only be inserted in one direction.

2. Access the camera's web interface to enable the onboard storage feature. For more information, see the *Pelco Sarix Enhanced 4 and 4P Bullet Operations Manual*.

Configuring the Camera

Once installed, use one of the following methods to configure the camera:

- If you have installed multiple cameras, you can use the Camera Configuration Tool to configure common settings. For more information, see the Camera Configuration Tool User Guide.
- If the camera is connected to the Avigilon Unity Video Client or Avigilon Control Center system, you can use the client software to configure the camera. For more information, see the Avigilon Control Center Client User Guide.
- If the camera is connected to a third-party network management system, you can configure the camera's specialty features in the camera's web browser interface. For more information, see the Avigilon IP Camera Web Interface User Guide.

For More Information

Additional information about setting up and using the device is available in the following guides:

- *Pelco Sarix Enhanced 4 and 4P Bullet Operations Manual* available on the Pelco website: www.pelco.com.
- *Camera Configuration Tool User Guide*

Connecting to Power and External Devices


If PoE is not available, the camera may be powered through the auxiliary power cable using 12 V DC. The power consumption information is listed in the product specifications.



IMPORTANT

This product is intended to be supplied by a UL Listed Power Unit marked “Class 2” or “LPS” or “Limited Power Source” with output rated 12 – 24VDC, 13 W min. or PoE rated 48 V DC, 13 W min. The camera must not be powered with 24 VAC aux power or the camera could be physically damaged.

External devices are connected to the camera through pluggable terminal blocks. For the locations of the terminals, see [Overview on page 1](#). The pinout for the I/O terminal block is shown in the following diagram:



1. Digital Output
2. Ground
3. Digital Input
4. Voltage Output (Max 50mA)
5. Audio Ground
6. Audio Input (line level)
7. Audio Output (line level)

AUX1 – Auxiliary Power Wire. Takes DC aux power only.

AUX2 – Auxiliary Power Wire. Takes DC aux power only.

* – Relay

** – Switch

M – Microphone

S – Speaker

External Power Failover

If the camera has power available from both an external Aux power supply and a PoE PSE (Power Sourcing Equipment) device, the camera will draw power from Aux. In the event that the camera loses power from the preferred Aux power supply it can transition to drawing power from the PoE PSE device.

SRXE4 and SRXE4P camera models respond differently if they lose power from the preferred Aux power supply. If an SRXE4P camera loses power from the preferred Aux power supply, the camera is capable of a Seamless Failover, meaning the SRXE4P can switch to drawing power from the PoE PSE device without interruption. Conversely, the SRXE4 camera models experiences a Non-Seamless Failover, meaning the camera may power off while waiting to transition to PoE power.

Non-Seamless Failover for SRXE4 models

If the camera loses Aux power, the camera will power-off while waiting to transition to PoE power. If the external Aux power re-energizes, the camera might reboot while transitioning back to using Aux power. The camera might not reboot if the external Aux power supply reacts quickly enough to the increase in load.



NOTE

Ensure that sufficient power is manually reserved on the PSE, as the camera will not request PoE power until the camera loses Aux power.

Seamless Failover for SRXE4P models

Seamless failover allows the camera to transition between PoE and auxiliary power sources without any interruption of camera operation or video recording. This is mainly useful if you want redundant power sources so that backup power will be available if one power source goes down.



NOTE

Seamless failover is only guaranteed when PoE Class 4 (25.5W) "full power" is available on the PoE port. Auxiliary (Aux) power is always assumed to be "full power," meaning that there is enough power available for all possible camera functions. PoE, on the other hand, has many different power classes and the product's functionality depends on the PoE power class that is available.

If the PSE demotes the camera to PoE Class 3 (13W), the camera will boot and display an "insufficient power" message. Therefore, if the camera is connected to a Class 3 PoE source while running on Aux power and using full IR power and the Aux power source is disconnected, the camera will most likely overload the PSE and reboot. However, if the camera is not using IR LEDs and Aux power is removed, the Class 3 PoE power source would be adequate to guarantee seamless failover.



IMPORTANT

There is a downside to having seamless failover if you aren't using this functionality and are connecting your cameras to PoE-enabled switches while running the camera on Aux power. Since the PoE connection remains active when running on Aux power, if the camera is connected to a PoE-enabled port on a switch, the switch by default will allocate some of its overall power budget to that port.

Connection Status LED Indicators

Once connected to the network, the green Connection Status LED indicator will display the progress in connecting to the Video Management System (VMS) software.

The following table outlines the different LED signals:

Connection State	Connection Status LED Indicator	Description
Obtaining IP Address	One short flash every second	Attempting to obtain an IP address.
Discoverable	Two short flashes every second	Obtained an IP address but not connected to the Network Video Management software.
Upgrading Firmware	Two short flashes and one long flash every second	Updating the firmware.
Connected	On	Connected to the Network Video Management software. The default connected setting can be changed to Off using the camera's web user interface. For more information, see the <i>Pelco Sarix Enhanced 4 and 4P Bullet Operations Manual</i> .

Troubleshooting Network Connections and LED Behavior



NOTE

For any of the below LED behaviors, ensure that the camera is getting power and is using a good network cable before trying another solution.

LED Behavior	Suggested Solution
Green LED is off and amber is on	Perform a factory reset of the camera using the physical firmware revert button. Resetting through the camera's web interface will not produce the desired result.
Both LEDs are off and the camera is not connected or streaming video	If the LEDs are not disabled, perform a factory reset of the camera using the physical firmware revert button. Resetting through the camera's web interface will not produce the desired result.
Both LEDs are blinking several times at the same time, then pause and repeat the blinking	Perform a factory reset of the camera using the physical firmware revert button. Resetting through the camera's web interface will not produce the desired result.

LED Behavior	Suggested Solution
A different LED blinking pattern than those described above	Perform a factory reset of the camera using the physical firmware revert button. Resetting through the camera's web interface will not produce the desired result.

Resetting to Factory Default Settings

If the device no longer functions as expected, you can choose to reset the device to its factory default settings.

Use the firmware revert button to reset the device. The firmware revert button is shown in the following diagram:

For models that feature an SD card slot, resetting the camera will not affect video that has been recorded to the SD card.




Figure 1: The firmware revert button in the Configuration Panel.

1. Ensure the camera is powered on.
2. Unscrew the configuration panel cover on the bottom of the camera.
3. Using a straightened paperclip or similar tool, gently press and hold the firmware revert button for 3 seconds.
4. Screw the configuration panel cover back into place.



CAUTION

Do not apply excessive force. Inserting the tool too far may damage the camera.

Limited Warranty and Technical Support

Pelco warranty terms for this product are provided at pelco.com/warranty.

Warranty service and technical support can be obtained by contacting Pelco Technical Support:
pelco.com/contact.

Pelco Troubleshooting Contact Information

For further assistance, contact Pelco Product Support at 1-800-289-9100 (USA and Canada) or +1-559-292-1981 (international).

Do not try to repair the unit yourself. Leave maintenance and repairs to qualified technical personnel only.

