


GODOX 神牛 LED 产品			
产品系列	RGB-LED		
产品类型	RGB LED灯	RGB LED灯	RGB LED灯
产品型号	705-LED6R-00	版本	A
规格尺寸(mm)	规格尺寸(mm)		
尺寸(mm)	尺寸(mm)		
重量	重量		
工作电压	工作电压		
功率	功率		
使用寿命	使用寿命		
保修期	保修期		
认证	认证		

LITEMONS

RGB LED摄影灯 RGB LED Video Light

LED 6R



使用手册
Instruction Manual

前言

RGB LED摄影灯LED6R，有RGB彩光模式、双色温模式、特效灯光模式，可调节对应参数数值获得各种光效。适用于微距拍摄、视频拍摄、微电影、直播、视频会议、人像拍摄、静物拍摄等。可安装在相机热靴槽使用、或者独立使用、也可以组合使用，操作简单、轻巧便携。


主要特点：

- 多种功能，自由切换 LED双色温模式、彩光模式和13种情景光效模式。
- 自由调节色温、亮度、色彩饱和度。
- 内置锂电池，Type-C USB接口充电。
- 背部磁性吸附功能，可吸附在铁质物品表面使用。
- 带一个冷靴安装座和三个冷靴槽，可安装在热靴或者冷靴槽里使用，冷靴槽可组合多个灯或有其他器材配件使用。
- 外观时尚，操作简单，轻巧便携。

警告

- △ 本产品不能防水，在雨天及潮湿环境下请注意防水。
- △ 请勿在化学品、可燃性气体或其他特殊物质附近使用灯，有可能导致火灾或电路干扰。在这些场合下，请注意相关警告标识。
- △ 内置锂电池，禁止拆卸、撞击、挤压或投入火中，若出现严重膨胀，请勿继续使用。请勿放置在超过-10℃-40℃的环境中。使用产品要求参数的充电器进行充电，并且正确的按照操作说明，在规定的电压、温度范围内使用。

部件



- 01. 灯珠
- 02. 柔光片
- 03. 1/4螺孔冷靴安装座
- 04. Type-C USB充电接口
- 05. 冷靴槽
- 07. 开关按钮
- 08. 模式选择按钮
- 09. 调节按钮
- 10. 光效按钮
- 11. 显示屏

标配物品

- 灯体 *1
- Type-C USB线 *1
- 柔光罩 *1
- 说明书 *1

电池

1. 本品采用1800mAh锂电池，内置在产品里面不可拆卸，使用寿命长。
 2. 安全可靠，内置电路有过充保护、过放保护、过流保护、短路保护。
 3. 使用5V 2A充电器充电，屏幕中的电池图标不闪烁为充满。
- 注意事项：
1. 充电不要放置超过24小时。
 2. 应放置于凉爽、干燥、通风的地方储存。
 3. 不要靠近凉爽、干燥、通风的地方储存。
 4. 电池使用幅度后请按当地的规定处理。
 5. 长期不使用，请充放电70%再放置。
 6. 为了延长电池使用寿命，建议每3个月进行一次充保养。
 7. 电池有一定的寿命限制，使用一定时间后，性能会减弱，属正常现象。

操作说明

1. 灯设置

- 1.1. 开/关机
开关推钮至ON，灯打开，屏幕显示主机当前灯光参数信息，推至OFF灯关闭。

- 1.2. 模式选择：双色温模式/彩光模式/情景光效模式
长按M按钮切换模式：显示屏上显示为CCT即双色温模式。



显示HSI即为彩光模式。

按FX按钮进入情景光效模式，显示13种光效序号和图标。

1.3. 固定和拓展

通过冷靴座可固定在带冷靴/热靴的物品上。通过冷靴座的1/4" 螺孔孔固定在带1/4" 螺孔的物品上（如云台、三脚架、灯架）。背部有磁铁，可吸附在铁质物品表面使用。三个冷靴槽可拓展带冷靴座的物品。多个灯可组合在一起使用。



2. 双色温模式: 长按M按钮选择。

- 2.1 短按M按钮选择要调整的数值，选中反色显示。

- 2.2 色温调节：上调节按钮 增加色温值，下调节按钮 降低色温值，短按一次数值变动100K，长按快速调节，调节范围3200K～6500K。
- 2.3 亮度调节：上调节按钮 增加亮度值，下调节按钮 降低亮度值，短按一次数值变动1%，长按快速调节，调节范围0～100%。


3. 彩光模式: 长按M按钮选择。

- 2.1 短按M按钮选择要调整的数值，选中反色显示。

- 3.2 调节色相H：上调节按钮 增加色相值，下调节按钮 降低色相值，短按一次数值变动1°，长按快速调节，色相调节范围0～360°。
- 3.3 调节饱和度S：上调节按钮 增加饱和度值，下调节按钮 降低饱和度值，短按一次数值变动1%，饱和度调节范围0-100%。
- 3.4 亮度调节：上调节按钮 增加亮度值，下调节按钮 降低亮度值，短按一次数值变动1%，长按快速调节，调节范围0～100%。

4. 情景光效模式

- 4.1 按Fx按钮进入情景光效模式，短按Fx按钮13种光效循环切换，长按快速循环；
- 4.2情景光效模式13种：可根据需求选择。



产品参数

型号	LED6R
内置锂电池	1800mAh
充电电压	5V/2A
功率	最大6W
色温范围	3200K～6500K
100%光亮度(LUX@0.5米)(m)	270
CRI(=)	95
显光范围	0%～100%
持续使用时间	2H-10H
工作环境温度	-10-40℃
产品尺寸	77*66*30 mm
净重	110g

维护保养

- 灯体在工作时，如发现异常，应立即关掉电源，查明原因。
- 灯体应避免震动，平时注意表面除尘。
- 灯体有发热为正常现象，无特别异常时，勿连续引内。
- 维修由各大指定售后服务原厂配件之维修部负责。
- 本产品保修一年，消耗品不在一年保修范围内，内置电池保修六个月。
- 如发生、漏油维修此灯，将取灯灯一年保修期，维修需收取相关费用。
- 如果本品出现故障或被水淋湿，在专业人员进行维修后方可继续使用。
- 设计和规格如有变更，恕不另行通知。

合格证
QC PASS

LITEMONS

产品保修

尊敬的用户，本保修卡是申请保修服务的重要凭证，请您妥善保管填写并妥善保管，谢谢！

产品信息	型号	产品条码
用户信息	姓名	联系电话
	通信地址	
销售商信息	名称	联系电话
	通信地址	
	销售日期	
备注		

注：此表应由销售商盖章确认。

适用产品

本文档适用于型号《产品保修信息》（见后面说明列明）产品，其他非此范围的产品或部件(如促销品、赠品及其他出厂后附加的配件等)不在此保修承诺内。

保修期

产品及附件的相应保修期限相关的《产品保修信息》执行。保修期自产品首次购买日起算，购买日以购买产品时保修卡登记日期为准。

如何获得保修服务

保修服务，您可直接或与产品销售商或授权服务机构联系，也可拨打神牛售后服务热线，与我们联系。我们的服务人员为您提供保修、申请保修时，您需提供有效的保修卡作为保修凭证，方可获得保修，如您不能提供有效的保修卡，而在我们确认产品品质属于保修范围的情况下，也可以为您提供保修，但不作为我们的义务。

不适用保修的情况

如产品存在下列情况，本文件项下的保证和服务将不适用：①产品或部件超过保修期；②错误或不适当使用，维护或维修导致的损坏或部件损坏；③不当地面：非正常使用或预期用途使用；④不当操作或外部损坏；⑤跌落或外力挤压；⑥接触或暴露于水或潮湿、酸、碱、溶剂、腐蚀性物质或液体；⑦由非神牛授权机构或人员安装、修理、更改、添加或拆卸造成的损坏或部件损坏；⑧产品部件故障有非自然因素或意外造成或丢失；⑨无有效保修卡；⑩使用非合法授权、非标准或非公开发行的软件造成的数据或损坏；⑪因不可抗力或意外事件造成的损坏或部件损坏；⑫其他非因产品本身质量问题导致的故障或损坏。遇上述情况，您应向相关责任方寻求解决，神牛对此不承担责任或义务。若您发现故障或损坏范围内的故障，附件或软件仅做产品不能正常使用的，不是保修范围内的故障，产品使用过程中正常的损耗、磨损和消耗，不是保修范围内的故障。

产品保修和服务支持信息
产品的保修期和服务类型按以下《产品保修信息》执行：

Forward

This RGB LED Video Light LED6R is a multifunctional RGB light with multicolor, dual color temperature, FX lights effects which can be wirelessly adjusted. Suitable for almost all shooting occasions e.g. live, make up, portrait and product shooting, video and recording, etc. It can be used on camera independently or in combination with easy operation and great portability.


Main Features

- Freely switch LED CCT mode, RGB recycle mode and FX light effects mode
- Easy to adjust color temperature, brightness and color saturation
- With built-in lithium battery and the light can be charged through Type-C USB port
- With magnetic absorbed function which enables the light can be absorbed onto the iron surface
- Can be used independently or in combination with cold shoe mounting base and slots
- Fashionable, easy operated and portable

Warning

- △ As this product do not have waterproof function, please take measures of waterproof in rainy or damp environment.
- △ Do not use the flash unit in the presence of flammable gases, chemicals and other similar materials. In certain circumstance, these materials may be sensitive to the strong light emitting from this flash unit and fire or electromagnetic interference may result.
- △ As this product has built-in lithium battery, do not disassemble, impact,squeeze or put it into fire. If serious bulge occurs, please do not use. Do not use or store the product if the ambient temperature reads over the range of -10°C to 40°C. Please charge the product with included adapter and correctly operate it within the defined voltage and working temperature according to the instruction manual.

Names of Parts



- 01. LED Beads
- 02. Diffusion
- 03. 1/4" Cold Shoe Mounting Base
- 04. Type-C USB Charging Port
- 05. Cold Shoe Slot
- 06. Cold Shoe Base
- 07. Power Switch
- 08. Mode Selection Button
- 09. Adjustment Button
- 10. Light Effects Button
- 11. Display

What's in the Box

- Light Body *1
- Type-C USB Cable *1
- Diffuser *1
- Instruction Manual *1

Battery

1. This flash unit has built-in 1800mAh Li-ion battery which is non-detachable.
2. It is reliably safe. The inner circuit is against overcharge, overcurrent, overheat, and short circuit.
3. Charge the battery by using the 5V 2A charger.

Cautions:

1. No over 24 hours' continuous charging.
2. Store in dry, cool, ventilated places.
3. Do not put aside or into fire.
4. Dead batteries should be disposed according to local regulations.
5. Please charge the battery to approx. 70% before being placed for long time.
6. If the battery had ceased using for over 3 months, please make a full recharge.
7. It's normal that the battery will be degraded after a period's usage for the battery life limitation.

Operation

1. Light Setting

- 1.1 Power ON/OFF
Please push the power switch onto **ON** to power on the light and the current parameters will be displayed. Push the power switch to OFF to power the light off.

1.2 Mode Selection: CCT Mode/Colorful Mode/ Light Effects Mode

Long press the M button to switch different modes: displayed CCT means bi-color mode and HSI means colorful mode.

Press FX button to enter light effects mode and 13 categories modes and icons will be displayed.

1.3 Installation and Multi Usage

The light can be fixed on the equipment with cold shoe or hot shoe through its cold shoe mounting base. It can be fixed on the equipment with 1/4"sockets e.g. pan-tilt, tripod and light stand. With built-in magnet in its back, this light can be absorbed on the subjects with iron surface. And the three cold shoe sockets enable this light to be installed on the equipment with cold shoe mounting base.



2. CCT mode: long press the M button to choose this mode.

- 2.1 Short press the M button to choose the value to be adjusted.

- 2.2 Color temperature adjustment: press the upper adjustment button to increase the color temperature value while lower button to decrease. Short press the button once and the color temperature value will changes in 100K. Long press the button to adjust the value from 3200K to 6500K quickly.
- 2.3 Brightness adjustment: press the upper adjustment button to increase the brightness value while lower button to decrease. Short press the button once and the color temperature value will changes in 1%. Long press the button to adjust the value from 0 to 100% quickly.

3. Colorful mode: long press the M button to choose this mode.

- 3.1 Short press the M button to choose the value to be adjusted.
- 3.2 H hue adjustment: press the upper adjustment button to increase the hue value while lower button to decrease. Short press the button once and the saturation value will changes in 1°. Long press the button to adjust the value from 0 to 360° quickly.
- 3.3 Saturation adjustment: press the upper adjustment button to increase the saturation value while lower button to decrease. Short press the button once and the saturation value will changes in 1. Long press the button to adjust the value from 0 to 100 quickly.
- 3.4 Brightness adjustment: press the upper adjustment button to increase the brightness value while lower button to decrease. Short press the button once and the brightness value will changes in 1%. Long press the button to adjust the value from 0 to 100% quickly.

Technical Data

Model	LED6R
Built-in Lithium Battery	1800mAh
Power Source of Charging	5V/2A
Power	Max. 6W
Color Temperature Range	3200K - 6500K
100% Illuminance(LUX@0.5m)(m)	270
CRI(=)	95
Brightness Range	0%~100%
Duration	2H-10H
Working Environment Temperature	-10-40℃
Dimension	77*66*30 mm
Net Weight	110g

Maintenance

- Shut down the device immediately should abnormal operation be detected.
- Avoid sudden impacts and the product should be dedusted regularly.
- It is normal for the light beads to be warm when in use. Avoid continue flashes if unnecessary.
- Maintenance of the light must be performed by our authorized maintenance department which can provide original accessories.
- This product, except consumables, is supported with a one-year warranty. Lithium battery is supported with six months warranty.
- Unauthorized service will void the warranty.
- If the product had failures or was wetted, do not use it until it is repaired by professionals.
- Changes made to the specifications or designs may not be reflected in this manual.

Warranty

Dear customers, as this warranty card is an important certificate to apply for our maintenance service, please fill in the following form in coordination with the seller and shipping it. Thank you!

Product Information	Model	Product Code Number
Customer Information	Name	Contact Number
	Address	
Seller Information	Name	Contact Number
	Address	
	Date of Sale	
Note:		

Note: This form shall be sealed by the seller.

Applicable Products

The document applies to the products listed on the **Product Maintenance Information** (see below for further information). Other products or accessories (i.e. promotional items, upgrades and additional accessories attached etc.) are not included in this warranty scope.

Warranty Period

The warranty period of products and accessories implemented according to the relevant **Product Maintenance Information**. The warranty period is calculated from the original date when the product is brought into the market. The purchase date is considered as the date registered on the warranty card when buying the product.

How to Get the Maintenance Service

If maintenance service is needed, you can directly contact the product distributor or authorized service institutions. You can also contact the Godox after-sale service call and we will offer you service. When applying for maintenance service, you should provide valid warranty card. If you cannot provide valid warranty card, we may offer you maintenance service once confirmed that the product or accessory is involved in the maintenance scope, but that shall not be considered as our obligation.

Inapplicable Cases

The guarantee and service offered by this document are not applicable in the following cases: 1. The product or accessory has expired its warranty period.; 2. Breakage or damage caused by inappropriate usage, maintenance or operations, such as improper packing, improper usage, improper playing, misol external equipment, falling off or exposure to external force, contacting or exposing to the improper temperature, solvent, acid, base, flooding and damp environment, etc.; 3. Breakage or damage caused by non-authorized institutions or staff in the process of installation, maintenance, alteration, addition and detachment.; 4. The original identifying information of product or accessory is modified, altered, or removed.; 5. No valid warranty card.; 6. Breakage or damage caused by using illegally authorized, nonstandard or non-public released software.; 7. Breakage or damage caused by force majeure or accident.; 8. Breakage or damage that could not be attributed to the product itself. Once met these situations above, you should seek solutions from the relevant responsible parties and fulfill your own responsibility. The damage caused by parts, accessories and software that beyond the warranty period or scope is not included in our maintenance scope. The normal deterioration, abnormal use and consumption are not the scope within the maintenance scope.

Maintenance and Service Support Information
The warranty period and service types of products are implemented according to the following **Product Maintenance Information**.

Product Name	Maintenance Period (month)	Warranty Service Type
Parts		
Circuit Board	12	Customer sends the product to designated site
Battery	3	Customer sends the product to designated site
Electrical parts e.g. battery charger, power cord, fire cable, etc.	12	Customer sends the product to designated site
Other Items		
Flash tube, modeling light, fire body, lamp cover, lighting device, etc.	No	Without warranty

Godox After-Sale Service Call 0755-29609320-8062