

Dual V-mount Adapter
INTRODUCTION

THANK YOU FOR CHOOSING GENARAY

Genaray's BA-VMOUNT is a dedicated dual V-mount battery adapter for the Genaray Powerhouse. It accepts two 14.4-14.8-volt batteries and is equipped with a 60 volt, 5-pin output. The light-stand clamp allows you to conveniently secure the adapter to a light stand to keep it out of the way and avoid cable clutter.

PRECAUTIONS



- Please read and follow these instructions, and keep this manual in a safe place.
- Keep this unit away from water and any flammable gases or liquids.
- Use only the correct, recommended voltage.
- Do not attempt to disassemble or repair the equipment—doing so will void the warranty, and Genaray will not be responsible for any damage.
- Handle the unit with care.
- Clean the unit with only a soft, dry cloth.
- Keep this unit away from children.
- Use only parts provided by the manufacturer.
- Make sure the item is intact and that there are no missing parts.
- All images are for illustrative purposes only.

PRODUCT
OVERVIEW



PRODUCT
SPECIFICATIONS

Battery Mount: V-mount (x2)

Input Voltage: DC 14.4-14.8V (x2)

Output Voltage: DC 24 V
DC 60 V

Connector: 3-pin XLR (24 V)
5-pin XLR (60 V)

Dimensions (H x W x D): 6.6 x 4.8 x 3.4 in.
(16.8 x 12.2 x 8.6 cm)

Weight: 1.5 lb. (680 g)

OPERATING THE BA-VMOUNT

Important ⚠️

The BA-VMOUNT will operate only with two 14.4-14.8-volt V-mount batteries installed. Do not attempt to power your Genaray light using a single V-mount battery.

Slide each battery into the V-mount until it locks into place.

To remove a battery, press the battery release and slide it out of the mount.

To attach the BA-VMOUNT to a light stand, loosen the wing nut, and open the clamp. Close the clamp around the light stand, and tighten the wing nut until secure.



POWERING A LIGHT

Important ⚠️

Do not attempt to power two lights from the 24 V and 60 V outputs simultaneously.

Use the 5-pin XLR cable that's included with the Powerhouse to connect the light to the BA-VMOUNT.

Note:

Do not use the 3-pin, 24 V output to power Genaray's Endeavor LED monolight. To power the Endeavor, use the Genaray BA-VMOUNT-E Dual V-mount Adapter.

To unplug the XLR cable, press the cable release tab and remove the connector.

ONE-YEAR LIMITED WARRANTY

This Genaray product is warranted to the original purchaser to be free from defects in materials and workmanship under normal consumer use for a period of one (1) year from the original purchase date or thirty (30) days after replacement, whichever occurs later. Genaray's responsibility with respect to this limited warranty shall be limited solely to repair or replacement, at Genaray's discretion, of any product that fails during normal use of this product in its intended manner and in its intended environment. Inoperability of the product or part(s) shall be determined by Genaray. If the product has been discontinued, Genaray reserves the right to replace it with a model of equivalent quality and function.

This warranty does not cover damage or defect caused by misuse, neglect, accident, alteration, abuse, improper installation or maintenance. EXCEPT AS PROVIDED HEREIN, GENARAY MAKES NEITHER ANY EXPRESS WARRANTIES NOR ANY IMPLIED WARRANTIES, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. This warranty provides you with specific legal rights, and you may also have additional rights that vary from state to state.

To obtain warranty coverage, contact the Genaray Customer Service Department to obtain a return merchandise authorization ("RMA") number, and return the defective product to Genaray along with the RMA number and proof of purchase. Shipment of the defective product is at the purchaser's own risk and expense.

For more information, or to arrange service, visit www.genaray.com or contact us at info@genaray.com.