

RF100

Hand Controller



SPECIFICATIONS

- RF hand controller is runned by 9V battery.
- Upto 10 pcs of prompts can be controlled at a time in the same place by using the 10 different channel options on the RF hand controller.
- Moreover one receiver can be controlled by more than one controller. Plus, whichever is used can be controlled even if all are open.
- Set up is utmost easy; place and run!
- There is an ergonomic sliding pot that helps to arrange the speed of the text.
- Besides an extra battery save is provided by the help of the on-off button on the hand controller.
- The red led light will flash constantly once the battery of the hand controller is 20%.



R100 Receiver

FORTINGE

www.fortinge.com

fb.com/fortingevideo

Zümrütevler Mh. Ertuğrul Sk. No:10

Akratek Plaza

Maltepe - Istanbul / Turkey

+90 (216) 418 11 03

info@fortinge.com

Záhony u. 7. Graphisoft Park D épület 1. emelet 1031 Budapest, Hungary

sales@fortinge.com